

### **BRISTOL 400 FUEL SENDER VIEW FROM BACK OF TANK**

Sender coil should measure approx 85 ohms with tank full, and 0 ohms when empty.

#### **FLOAT DETAILS**

Scale 1:1 inches

Materials: Arm : 5/64ths (2 mm) dia. music steel. Length centre pivot to centre line of float = 11"

Ties and clamps : 26 ga. (.3 mm) brass

Float: 1-1/4" dia x 3" long: tinplate steel - soldered joints, with arm through centre (at right angles).

#### **SENDER DETAILS**

Smiths 64509

Screw size (to tank) - 3 BA x 3/8"

